



making waves in a wire-free world

# Wireless Panic Button



Single button or dual-push wireless PA UHF transmitter with key-switch reset



Transmit to pagers and/or fixed receivers

## Fixed Panic Button

Designed for wall or under-desk mounting, the panic transmitter sends a repeating signal when activated until reset with a key. An LED indicator flashes periodically to indicate that the unit is in its triggered state. The unit is also available as a single-shot unit without a reset facility.

Multiple units can be used on a site, each sending its own unique identifier to the receiving devices, which could be pagers, fixed receivers with relay outputs, or a combination of both.

UHF SRD radio transmitter with a range of up to 200 metres (dependent on site conditions)

Powered by a standard 9V PP3 alkaline battery.

## Compliance:

CFR47 Part 90. FCC ID: JRNUSAWAVETRACK  
EN 300 220, EN 301 489



## SPECIFICATIONS

- Power: 9V alkaline battery
- Current: Transmit: <50mA @ 10mW  
Sleep Mode: <20 uA
- Operating Temp: -30 to +50 deg C
- Tx Frequency Range: 430 - 470 MHz
- Tx Power: 10mW max
- Channel Spacing: 12.5KHz @ 2.5 KHz deviation
- Tx Baud: 512 / 1200
- Protocol: POCSAG
- Footprint: 60 (W) x 80 (L) x 43 (D) mm (excluding tabs)

## PART CODES

- SB1B Single button unit without keyswitch
- PB1B Single button unit with keyswitch reset
- PB2B Dual push unit with keyswitch reset

Dual-push unit with keyswitch reset



Single button unit with optional keyswitch reset



Scope Communications UK Ltd  
Quantum House  
Steamer Quay  
Totnes, Devon, TQ9 5AL  
England

Tel: +44 (0) 1803 860700  
Fax: +44 (0) 1803 863716  
Web: [www.scope-uk.com](http://www.scope-uk.com)  
Email: [sales@scope-uk.com](mailto:sales@scope-uk.com)